


Ebony Current Transformers



M93S RANGE

Case size: 90 mm wide x 30 mm deep x 131 mm high
 3.5" wide x 1.2" deep x 5.1" high
 Aperture: 76.5 x 19 mm, 60 x 30 mm
 3.0" x 0.7", 2.4" x 1.2"
 Weight: 0.7kg

DIMENSIONS



- Mounting feet centres
71.5 mm x 51 mm

Model type	Primary current	VA at Class 3	VA at Class 1	VA at Class 0.5
M93S-800/5A	800	10	10	5
M93S-1000/5A	1000	150	10	7.5
M93S-1200/5A	1200	20	15	10
M93S-1250/5A	1250	20	20	15
M93S-1500/5A	1500	20	20	15
M93S-1600/5A	1600	30	20	15
M93S-2000/5	2000	30	20	15

ORDERING CODES


As above	Change end suffix to depict required secondary. For example: M93S-1000/1
M50-DINCLIP	DIN-rail mounting clip for DIN-rail mounting option (2 required)



S95P RANGE

Case size: 90 mm wide x 50 mm deep x 144 mm high
 3.5" wide x 2" deep x 5.7" high
 Weight: 0.9kg - 1.1kg

DIMENSIONS



- Mounting feet centres
71.5 mm x 71 mm

Model type	Primary current	VA at Class 1
S95P-5/5	5 + 5 = 5	5
S95P-5/5/5	5 + 5 + 5 = 5	5

ORDERING CODES


As above	Change end suffix to depict required secondary. For example: S95P-1/1
M50-DINCLIP	DIN-rail mounting clip for DIN-rail mounting option (2 required)



S97P RANGE

Case size: 90 mm wide x 50 mm deep x 144 mm high
 3.5" wide x 2" deep x 5.7" high
 Weight: 0.9kg - 1.1kg

DIMENSIONS



- Mounting feet centres
71.5 mm x 91 mm

Model type	Primary current	VA at Class 1
S97P-5/5/5/5	5 + 5 + 5 + 5 = 5	5
S97P-5/5/5/5/5	5 + 5 + 5 + 5 + 5 = 5	5
S97P-5/5/5/5/5/5	5 + 5 + 5 + 5 + 5 + 5 = 5	5

ORDERING CODES

As above	Change end suffix to depict required secondary. For example: S95P-1/1
----------	---

Consult factory for availability and lead time on 1A secondary.